



## 4-Port USB KVM Switch with Audio

Vision I 331514

### | Specifications

|                     |  |
|---------------------|--|
| Interface           | USB 1.1  |
| PC Connection       | 4 x HDB15/F (combined w/USB interface)<br>8 x 3.5mm audio jack (speaker & mic)   |
| Console Connection  | 2 x USB A/F (keyboard & mouse)<br>1 x HDB15/F (monitor)<br>2 x 3.5mm audio jack (speaker & mic)                                    |
| Included Cables     | 4 x VGA/USB combo cable<br>(HDB15/M > HDB15/M + USB A/M)<br>4 x Audio combo cable<br>(2 x 3.5mm audio plug > 2 x 3.5mm audio plug) |
| PC Selection        | Push buttons / Hot keys / Switching software   |
| LED Indicators      | 4  |
| Max. Resolution     | 2048 x 1536  |
| Monitor Supported   | VGA, SVGA, XGA, QXGA, multi-sync monitors  |
| Power               | USB bus powered  |
| Physical Properties | Plastic Housing<br>Dimensions (L x W x H): 164 x 72 x 26mm   |

### | Key Features

- Controls 4 computer from a single keyboard, mouse, and monitor
- Provides Hot-key switching
- Supports wide screen displays
- Audio enabled, 2.1 surround sound support
- Plug-and-Play
- Supports WIN 98/ME/2000/XP/Vista/7, Mac OS V10.4 or above

### | Package Contents

- 1 x 4-Port USB KVM Switch
- 4 x 3-in-1 USB KVM Cable, 1.8m
- 4 x Audio/Mic Cable, 1.8m
- 1 x CD Driver
- 1 x Quick Installation Guide